



Installing Microsoft Windows 2000 - IBM IntelliStation M Pro (Type 6849)

Applicable countries and regions

Prerequisites

Windows 2000 Professional CD-ROM

System Preparation

If no data is on the system, a low level format on the SCSI hard disk drive is suggested. Skip to the installation section, if you do not have a SCSI hard disk drive.

NOTE: This will remove all data on the system.

1. Start the system, wait for the CTRL-A message from Adaptec (after the IBM logo), select **Channel A**
2. Select **SCSI Disk Utilities**
3. Select the **ID** for the hard disk drive you wish to format
4. Select **format** (approximately 30 minutes to complete)
5. Configure your system to boot from the CD-ROM:
 1. Restart system, press **F1** when prompted
 2. Select the **Boot** tab
 3. Select **Boot Device Priority**
 4. Set the first boot device to **Removable**, the second boot device to **ATAPI CD-ROM**, the third boot device to **Hard Disk Drive**, and the fourth boot device to **Disabled**.
 5. Press **F10** to Save and Exit. The system will now boot from the CD-ROM.

Installation

1. Start the system and insert the Windows 2000 Professional CD.
2. When prompted, press **any key** to boot from CD.
3. Welcome to Setup is the first screen, press **Enter** to continue.
4. Page down to read the End User License Agreement. If you accept the Terms and Conditions of the License Agreement, press **F8** to continue the installation process.
5. Choose or create a partition on which to install Windows 2000. Drive C: is suggested. Press **Enter** to continue.
6. Choose the NTFS or FAT file system (FAT recommended), press **Enter** to continue. Windows will examine your hard disk drive, copy any required files, and automatically restart your system.
7. The system will then restart to the graphical portion of setup (Windows 2000 Setup Wizard), and will display the "Welcome" window when Windows 2000 is fully loaded. Press **Next** to continue.
8. The "Regional Settings" window will appear. Configure for the appropriate locale and keyboard, press **Next** to continue.
9. Type your Name and Organization in the fields provided to personalize your software window. Press **Next** to continue.
10. Enter the Product Key number. Press **Next** to continue.
11. The "Computer Name and Administrator Password" window displays. Set the Computer Name and Administrative Password. Press **Next** to continue.

NOTE: Store the administrator password in a safe place. You will not be able to get into the system without it.
12. The date and time settings window displays. Set the **Time**, **Date**, and **Time Zone**. Press **Next** to continue.
13. In the "Network Settings" window, contact your network administrator for assistance with specific settings. Choose **Typical Settings**. Press **Next** to continue.
14. Connect to a domain or a workgroup, contact your network administrator for assistance with specific settings, press **Next**.
15. This portion of setup is complete, press **Finish**.

Drivers and BIOS updates

Audio Drivers: d64z21us.exe or most current

Network Drivers: No update needed

SCSI Drivers: No update needed

Bus master Drivers: No update needed

Core Chipset: No update needed
Video Drivers: Dependent on video card type. Please check on the support site for any updates.
BIOS: Always use the most current. Find updates at above URL.

Applicable countries and regions

Worldwide

[Back to top](#)

Document id: MIGR-41652
Last modified: 2009-06-10
Copyright © 2012 IBM Corporation
